Lecture 5: Constraint satisfaction: formalisms and modelling

- When solving a search problem the most efficient solution methods are typically based on special purpose algorithms.
- In Lectures 3 and 4 important approaches to developing such algorithms have been discussed.
- However, developing a special purpose algorithm for a given problem requires typically a substantial amount of expertise and considerable resources.
- Another approach is to exploit an efficient algorithm already developed for some problem through reductions.

Exploiting Reductions

- Given an efficient algorithm for a problem A we can solve a problem B by developing a reduction from B to A.



- Constraint satisfaction problems (CSPs) offer attractive target problems to be used in this way:
  - CSPs provide a flexible framework to develop reductions, i.e., encodings of problems as CSPs such that a solution to the original problem can be easily extracted from a solution of the CSP encoding the problem.
  - Constraint programming offers tools to build efficient algorithms for solving CSPs for a wide range of constraints.
  - There are efficient software packages that can be directly used for solving interesting classes of constraints.

Constraint Satisfaction Problems (CSPs)

- Given variables $Y := y_1, \ldots, y_k$ and domains $D_1, \ldots D_k$, a constraint C on Y is a subset of $D_1 \times \cdots \times D_k$.
- If $k = 1$, the constraint is called unary and if $k = 2$, binary.
- **Example.** Consider variables y_1, y_2 both having the domain $D_i = \{0, 1, 2\}$ and a binary constraint *NotEq* on y_1, y_2 such that $NotEq = \{(0,1), (0,2), (1,0), (1,2), (2,0), (2,1)\}$.
- For variables x, y, we denote this constraint modelling non-equality by $x \neq y$.
- Given variables $x_1, \ldots, x_n$ and domains $D_1, \ldots D_n$, a constraint satisfaction problem (CSP):

$$\langle \mathbf{C}; x_1 \in D_1, \ldots, x_n \in D_n \rangle$$

where $\mathbf{C}$ is a set of constraints each on a subsequence of $x_1, \ldots, x_n$.

CSPs II

- For a constraint C on $x_{i_1}, \ldots, x_{i_m}$, an n-tuple $(d_1, \ldots, d_n) \in D_1 \times \cdots \times D_n$ satisfies C if $(d_{i_1}, \ldots, d_{i_m}) \in C$
- **Example.** An n-tuple $(1, 2, \ldots, n)$ satisfies the constraint *NotEq* on x_1, x_2 because $(1, 2) \in NotEq$ but the n-tuple $(1, 1, \ldots, n)$ does not as $(1, 1) \notin NotEq$.
- A solution to a CSP $\langle \mathbf{C}, x_1 \in D_1, \ldots, x_n \in D_n \rangle$ is an n-tuple $(d_1, \ldots, d_n) \in D_1 \times \cdots \times D_n$ that satisfies each constraint $C \in \mathbf{C}$.

Example. Consider a CSP

$$\langle \{x_1 \neq x_2, x_1 \neq x_3, x_2 \neq x_3\}, x_1 \in \{0,1,2\}, x_2 \in \{0,1,2\}, x_3 \in \{0,1,2\} \rangle$$

The 3-tuple $(0, 1, 2)$ is a solution to the CSP as it satisfies all the constraints but $(0, 1, 1)$ is not because it does not satisfy the constraint $x_2 \neq x_3$.

Example. Coloring problem

Given a graph G, the coloring problem can be encoded as a CSP as follows.

- For each node v_i in the graph introduce a variable V_i with the domain $\{1,\ldots,n\}$ where n is the number of available colors.
- For each edge (v_i, v_j) in the graph introduce a constraint $V_i \neq V_j$.
- This is a reduction of the coloring problem to a CSP because the solutions to the CSP correspond exactly to the solutions of the coloring problem:
  a tuple $(t_1,\ldots,t_n)$ satisfying all the constraints gives a valid coloring of the graph where node v_i is colored with color t_i.

Example: SEND + MORE = MONEY

- Replace each letter by a different digit so that

```
  SEND          9567
+ MORE        + 1085
-------       ------
 MONEY        10652
```

  is a correct sum. The unique solution.
- Variables: S, E, N, D, M, O, R, Y
- Domains: [1..9] for S, M and [0..9] for E, N, D, O, R, Y
- Constraints:

$$\begin{aligned} &1000\cdot S + 100\cdot E + 10\cdot N + D \\ &+1000\cdot M + 100\cdot O + 10\cdot R + E \\ = &\ 10000\cdot M + 1000\cdot O + 100\cdot N + 10\cdot E + Y \end{aligned}$$

  $x \neq y$ for every pair of variables x, y in {S, E, N, D, M, O, R, Y}.
- It is easy to check that the tuple $(9,5,6,7,1,0,8,2)$ satisfies the constraints, i.e., is a solution to the problem.

N Queens

Problem: Place n queens on a $n \times n$ chess board so that they do not attack each other.

- Variables: $x_1,\ldots,x_n$ (x_i gives the position of the queen on ith column)
- Domains: [1..n]
- Constraints: for $i \in [1..n-1]$ and $j \in [i+1..n]$:
  (i) $x_i \neq x_j$ (rows)
  (ii) $x_i - x_j \neq i - j$ (SW-NE diagonals)
  (iii) $x_i - x_j \neq j - i$ (NW-SE diagonals)
- When $n = 10$, the tuple $(3,10,7,4,1,5,2,9,6,8)$ gives a solution to the problem.

Constrained Optimization Problems

- Given: a CSP $P := \langle \mathbf{C}; x_1 \in D_1,\ldots,x_n \in D_n\rangle$ and a function $obj : Sol \mapsto \mathbb{R}$
- (P, obj) is a constrained optimization problem (COP) where the task is to find a solution d to P for which the value $obj(d)$ is optimal.
- **Example.** KNAPSACK: a knapsack of a fixed volume and n objects, each with a volume and a value. Find a collection of these objects with maximal total value that fits in the knapsack.
- Representation as a COP:
  Given: knapsack volume v and n objects with volumes $a_1,\ldots,a_n$ and values $b_1,\ldots,b_n$.
  Variables: $x_1,\ldots,x_n$
  Domains: $\{0,1\}$
  Constraint: $\sum_{i=1}^{n} a_i \cdot x_i \leq v$,
  Objective function: $\sum_{i=1}^{n} b_i \cdot x_i$.

Solving CSPs

- Constraints have varying computational properties.
- For some classes of constraints there are efficient special purpose algorithms (domain specific methods/constraint solvers).
  Examples
  - Linear equations
  - Linear programming
  - Unification
- For others general methods consisting of
  - constraint propagation algorithms and
  - search methods

  must be used.
- Different encodings of a problem as a CSP utilizing different sets of constraints can have substantial different computational properties.
- However, it is not obvious which encodings lead to the best computational performance.

Constraints

- In the course we consider more carefully two classes of constraints: linear constraints and Boolean constraints.
- Linear constraints (Lectures 7–9) are an example of a class of constraints which has efficient special purpose algorithms.
- Now we consider Boolean constraints as an example of a class for which we need to use general methods based on propagation and search.
- However, boolean constraints are interesting because
  - highly efficient general purpose methods are available for solving Boolean constraints;
  - they provide a flexible framework for encoding (modelling) where it is possible to use combinations of constraints (with efficient support by solution techniques).

Boolean Constraints

- A Boolean constraint C on variables $x_1, \ldots, x_n$ with the domain $\{\textbf{true}, \textbf{false}\}$ can be seen as a Boolean function $f_C : \{\textbf{true}, \textbf{false}\}^n \longrightarrow \{\textbf{true}, \textbf{false}\}$ such that a tuple $(t_1, \ldots, t_n)$ satisfies the constraint C iff $f_C(t_1, \ldots, t_n) = \textbf{true}$.
- Typically such functions are represented as *propositional formulas*.
- Solution methods for Boolean constraints exploit the structure of the representation of the constraints as formulas.

Propositional formulas

- Syntax (what are well-formed propositional formulas):
  Boolean variables (atoms) $X = \{x_1, x_2, \ldots\}$
  Boolean connectives $\vee, \wedge, \neg$
- The set of (propositional) formulas is the smallest set such that all Boolean variables are formulas and if ϕ_1 and ϕ_2 are formulas, so are $\neg\phi_1$, $(\phi_1 \wedge \phi_2)$, and $(\phi_1 \vee \phi_2)$.
  For example, $((x_1 \vee x_2) \wedge \neg x_3)$ is a formula but $((x_1 \vee x_2)\neg x_3)$ is not.
- A formula of the form x_i or $\neg x_i$ is called a literal where x_i is a Boolean variable.
- We employ usual shorthands:
  $\phi_1 \longrightarrow \phi_2$: $\neg\phi_1 \vee \phi_2$
  $\phi_1 \leftrightarrow \phi_2$: $(\neg\phi_1 \vee \phi_2) \wedge (\neg\phi_2 \vee \phi_1)$
  $\phi_1 \oplus \phi_2$: $(\neg\phi_1 \wedge \phi_2) \vee (\phi_1 \wedge \neg\phi_2)$

Semantics

- Atomic proposition (Boolean variables) are either true or false and this induces a truth value for any formula as follows.
- A truth assignment T is mapping from a finite subset $X' \subset X$ to the set of truth values $\{\textbf{true}, \textbf{false}\}$.
- Consider a truth assignment $T : X' \longrightarrow \{\textbf{true}, \textbf{false}\}$ which is appropriate to ϕ, i.e., $X(\phi) \subseteq X'$ where $X(\phi)$ be the set of Boolean variables appearing in ϕ.
- $T \models \phi$ (T satisfies ϕ) is defined inductively as follows:
  If ϕ is a variable, then $T \models \phi$ iff $T(\phi) = \textbf{true}$.
  If $\phi = \neg\phi_1$, then $T \models \phi$ iff $T \not\models \phi_1$
  If $\phi = \phi_1 \wedge \phi_2$, then $T \models \phi$ iff $T \models \phi_1$ and $T \models \phi_2$
  If $\phi = \phi_1 \vee \phi_2$, then $T \models \phi$ iff $T \models \phi_1$ or $T \models \phi_2$

Example

Let $T(x_1) = \textbf{true}$, $T(x_2) = \textbf{false}$.
Then $T \models x_1 \vee x_2$ but $T \not\models (x_1 \vee \neg x_2) \wedge (\neg x_1 \wedge x_2)$

Representing Boolean Functions

- A propositional formula ϕ with variables $x_1, \ldots, x_n$ expresses a n-ary Boolean function f if for any n-tuple of truth values $\mathbf{t} = (t_1, \ldots, t_n)$, $f(\mathbf{t}) = \textbf{true}$ if $T \models \phi$ and $f(\mathbf{t}) = \textbf{false}$ if $T \not\models \phi$ where $T(x_i) = t_i$, $i = 1, \ldots, n$.

Proposition. Any n-ary Boolean function f can be expressed as a propositional formula ϕ_f involving variables $x_1, \ldots, x_n$.

- The idea: model the rows of the truth table giving **true** as a disjunction of conjunctions.
- Let F be the set of all n-tuples $\mathbf{t} = (t_1, \ldots, t_n)$ with $f(\mathbf{t}) = \textbf{true}$.
  For each $\mathbf{t}$, let $D_{\mathbf{t}}$ be a conjunction of literals x_i if $t_i = \textbf{true}$ and $\neg x_i$ if $t_i = \textbf{false}$.
- Let $\phi_f = \bigvee_{\mathbf{t} \in F} D_{\mathbf{t}}$

Example.

x_1	x_2	f
0	0	0
0	1	1
1	0	1
1	1	0

$\phi_f = (\neg x_1 \wedge x_2) \vee (x_1 \wedge \neg x_2)$

Logical Equivalence

Definition

Formulas ϕ_1 and ϕ_2 are equivalent ($\phi_1 \equiv \phi_2$) iff for all truth assignments T appropriate to both of them, $T \models \phi_1$ iff $T \models \phi_2$.

Example

$(\phi_1 \vee \phi_2) \equiv (\phi_2 \vee \phi_1)$
$((\phi_1 \wedge \phi_2) \wedge \phi_3) \equiv (\phi_1 \wedge (\phi_2 \wedge \phi_3))$
$\neg\neg\phi \equiv \phi$
$((\phi_1 \wedge \phi_2) \vee \phi_3) \equiv ((\phi_1 \vee \phi_3) \wedge (\phi_2 \vee \phi_3))$
$\neg(\phi_1 \wedge \phi_2) \equiv (\neg\phi_1 \vee \neg\phi_2)$
$(\phi_1 \vee \phi_1) \equiv \phi_1$

- Simplified notation:
  $(((x_1 \vee \neg x_3) \vee x_2) \vee x_4 \vee (x_2 \vee x_5))$ is written as
  $x_1 \vee \neg x_3 \vee x_2 \vee x_4 \vee x_2 \vee x_5$ or $x_1 \vee \neg x_3 \vee x_2 \vee x_4 \vee x_5$
- $\bigvee_{i=1}^{n} \varphi_i$ stands for $\varphi_1 \vee \cdots \vee \varphi_n$
  $\bigwedge_{i=1}^{n} \varphi_i$ stands for $\varphi_1 \wedge \cdots \wedge \varphi_n$

Normal Forms

- Many solvers for Boolean constraints require that the constraints are represented in a normal form (typically in conjunctive normal form).

Proposition. Every propositional formula is equivalent to one in conjunctive (disjunctive) normal form.

CNF: $(l_{11} \vee \cdots \vee l_{1n_1}) \wedge \cdots \wedge (l_{m1} \vee \cdots \vee l_{mn_m})$
DNF: $(l_{11} \wedge \cdots \wedge l_{1n_1}) \vee \cdots \vee (l_{m1} \wedge \cdots \wedge l_{mn_m})$
where each l_{ij} is a literal (Boolean variable or its negation).

A disjunction $l_1 \vee \cdots \vee l_n$ is called a clause.

A conjunction $l_1 \wedge \cdots \wedge l_n$ is called an implicant.

Normal Form Transformations

CNF/DNF transformation:

1. remove $\leftrightarrow$ and $\rightarrow$:
   $\alpha \leftrightarrow \beta \quad \rightsquigarrow \quad (\neg\alpha \vee \beta) \wedge (\neg\beta \vee \alpha) \quad (1)$
   $\alpha \rightarrow \beta \quad \rightsquigarrow \quad \neg\alpha \vee \beta \quad (2)$
2. Push negations in front of Boolean variables:
   $\neg\neg\alpha \quad \rightsquigarrow \quad \alpha \quad (3)$
   $\neg(\alpha \vee \beta) \quad \rightsquigarrow \quad \neg\alpha \wedge \neg\beta \quad (4)$
   $\neg(\alpha \wedge \beta) \quad \rightsquigarrow \quad \neg\alpha \vee \neg\beta \quad (5)$
3. CNF: move $\wedge$ connectives outside $\vee$ connectives:
   $\alpha \vee (\beta \wedge \gamma) \quad \rightsquigarrow \quad (\alpha \vee \beta) \wedge (\alpha \vee \gamma) \quad (6)$
   $(\alpha \wedge \beta) \vee \gamma \quad \rightsquigarrow \quad (\alpha \vee \gamma) \wedge (\beta \vee \gamma) \quad (7)$
   DNF: move $\vee$ connectives outside $\wedge$ connectives:
   $\alpha \wedge (\beta \vee \gamma) \quad \rightsquigarrow \quad (\alpha \wedge \beta) \vee (\alpha \wedge \gamma) \quad (8)$
   $(\alpha \vee \beta) \wedge \gamma \quad \rightsquigarrow \quad (\alpha \wedge \gamma) \vee (\beta \wedge \gamma) \quad (9)$

Example

Transform $(A \vee B) \rightarrow (B \leftrightarrow C)$ to CNF.

$(A \vee B) \rightarrow (B \leftrightarrow C) \quad (1,2)$
$\neg(A \vee B) \vee ((\neg B \vee C) \wedge (\neg C \vee B)) \quad (4)$
$(\neg A \wedge \neg B) \vee ((\neg B \vee C) \wedge (\neg C \vee B)) \quad (7)$
$(\neg A \vee ((\neg B \vee C) \wedge (\neg C \vee B))) \wedge (\neg B \vee ((\neg B \vee C) \wedge (\neg C \vee B))) \quad (6)$
$((\neg A \vee (\neg B \vee C)) \wedge (\neg A \vee (\neg C \vee B))) \wedge (\neg B \vee ((\neg B \vee C) \wedge (\neg C \vee B))) \quad (6)$
$((\neg A \vee (\neg B \vee C)) \wedge (\neg A \vee (\neg C \vee B))) \wedge ((\neg B \vee (\neg B \vee C)) \wedge (\neg B \vee (\neg C \vee B)$
$(\neg A \vee \neg B \vee C) \wedge (\neg A \vee \neg C \vee B) \wedge (\neg B \vee \neg B \vee C) \wedge (\neg B \vee \neg C \vee B)$

- We can assume that normal forms do not have repeated clauses/implicants or repeated literals in clauses/implicants (for example $(\neg B \vee \neg B \vee C) \equiv (\neg B \vee C)$).
- Normal form can be exponentially bigger than the original formula in the worst case.

Boolean Circuits

- Normal forms are often a quite unnatural way of encoding problems as a propositional formula.
- More natural encodings are obtained using Boolean circuits to represent the required Boolean functions
- A Boolean circuit C is a 4-tuple (V, E, s, α) where
- (V, E) is an acyclic graph whose nodes are called gates. The nodes are divided into three categories:
  - output gates (outdegree 0)
  - intermediate gates
  - input gates (indgree 0)
- s assigns a Boolean function $s(g)$ to each intermediate and output gate g of appropriate arity corresponding to the indegree of the gate.
- α assigns truth values to some gates.



Boolean Circuits—Semantics

- For a circuit a truth assignment $T : X(C) \longrightarrow \{\textbf{true}, \textbf{false}\}$ gives a truth assignment to each input gate $X(C)$ of C.
- This defines a truth value $T(g)$ for each gate g inductively if the gates are ordered topologically in a sequence so that no gate appears in the sequence before its input gates (this is always possible because the circuit is acyclic):
  - If $g \in X(C)$, then the truth assignment $T(g)$ gives the truth value.
  - Otherwise $T(g) = f(T(g_1), \ldots, T(g_n))$ where $(g_1, g), \ldots$ and (g_n, g) are the edges entering g and f is the Boolean function $s(g)$ associated to g.

Circuit Satisfiability Problem

- An interesting computational (search) problem related to circuits is the circuit satisfiability problem.
- Given a Boolean circuit (V, E, s, α) we say a truth assignment T satisfies the circuit if it satisfies the constraints α, i.e., for each gate g for which α gives a truth value, $\alpha(g) = T(g)$ holds.
- CIRCUIT SAT problem: Given a Boolean circuit find a truth assignment T that satisfies the circuit.

Example. Consider the circuit given on the right with constraints $\alpha(v_4) =$ **false** and $\alpha(v_1) =$ **true**. This circuit has a satisfying truth assignment $T(v_4) =$ **false**, $T(v_5) = T(v_6) =$ **true**.



Boolean Circuits vs. Propositional Formulas

- For each propositional formulae ϕ, there is a corresponding Boolean circuit C_ϕ such that for any T appropriate for both, $T(g_\phi) =$ **true** iff $T \models \phi$ for an output gate g_ϕ of C_ϕ .
  Idea: just introduce a new gate for each subexpression.

$(a \vee b) \wedge (\neg a \vee b) \wedge$
$(a \vee \neg b) \wedge (\neg a \vee \neg b)$



- For each Boolean circuit C, there is a corresponding formula ϕ_C.
- Notice that Boolean circuits allow shared subexpressions but formulas do not.

Circuits Compute Boolean Functions

- A Boolean circuit with output gate g and variables $x_1, \ldots, x_n$ computes an n-ary Boolean function f if for any n-tuple of truth values $\mathbf{t} = (t_1, \ldots, t_n)$, $f(\mathbf{t}) = T(g)$ where $T(x_i) = t_i$, $i = 1, \ldots, n$.
- Any n-ary Boolean function f can be computed by a Boolean circuit involving variables $x_1, \ldots, x_n$.
- Not every Boolean function can be computed using a concise circuit.

Theorem

For any $n \geq 2$ there is an n-ary Boolean function f such that no Boolean circuit with $\frac{2^n}{2n}$ or fewer gates can compute it.

Boolean Circuits as Equation Systems

A Boolean circuit can be written as a system of equations.



$v = \text{and}(e, f, g, h)$
$e = \text{or}(a, b)$
$f = \text{or}(b, c)$
$g = \text{or}(a, d)$
$h = \text{or}(c, d)$
$c = \text{not}(a)$
$d = \text{not}(b)$

Boolean Modelling

- Propositional formulas/Boolean circuits offer a natural way of modelling many interesting Boolean functions.
- Example. IF-THEN-ELSE $\text{ite}(a,b,c)$ (if a then b else c.).
  As a formula:
  $\text{ite}(a,b,c) \equiv (a \wedge b) \vee (\neg a \wedge c)$
  As a circuit:
  $i = \text{or}(i_1, i_2)$
  $i_1 = \text{and}(a, b)$
  $i_2 = \text{and}(a_1, c)$
  $a_1 = \text{not}(a)$
- Given gates a, b, c, $\text{ite}(a,b,c)$ can be thought as a shorthand for a subcircuit given above.
- In the `bczchaff` tool used in the course $\text{ite}(a,b,c)$ is provided as a primitive gate functions.

Example

Binary adder. Given input bits a, b and c
compute output bits $o_2 o_1$ which give the sum of a, b, and c in binary.

As a formula:

$o_1 \equiv ((a \oplus b) \oplus c)$
$o_2 \equiv (a \wedge b) \vee (c \wedge (a \oplus b)$

As a circuit:

$o_1 = \text{xor}(x, c)$
$o_2 = \text{or}(l, r)$
$l = \text{and}(a, b)$
$r = \text{and}(c, x)$
$x = \text{xor}(a, b)$

Encoding Problems Using Circuits

- Circuits can be used to encode problems in a structured way.
- Example. Given three bits a, b, c find their values such that if at least two of them are ones then either a or b is one else a or c is one.
- We use IF-THEN-ELSE and adder circuits to encode this as a CIRCUIT SAT problem as follows:
  $p = \text{ite}(o_2, x, p_1)$
  $p_1 = \text{or}(a, c)$
  `% full adder; gate` o_1 `omitted`
  $o_2 = \text{or}(l, r)$
  $l = \text{and}(a, b)$
  $r = \text{and}(c, x)$
  $x = \text{xor}(a, b)$
- Now each satisfying truth assignment for the circuit with $\alpha(p) =$ **true** gives a solution to the problem.

Example. Reachability

Given a graph $G = (\{1, \ldots, n\}, E)$, constructs a circuit $R(G)$ such that $R(G)$ is satisfiable iff there is a path from 1 to n in G.

- The gates of $R(G)$ are of the form
  g_{ijk} with $1 \leq i, j \leq n$ and $0 \leq k \leq n$
  h_{ijk} with $1 \leq i, j, k \leq n$
- g_{ijk} is **true**: there is a path in G from i to j not using any intermediate node bigger than k.
- h_{ijk} is **true**: there is a path in G from i to j not using any intermediate node bigger than k but using k.

Example—cont'd

$R(G)$ is the following circuit:

- For $k = 0$, g_{ijk} is an input gate.
- For $k = 1, 2, \ldots, n$:
  $h_{ijk} = \text{and}(g_{ik(k-1)}, g_{kj(k-1)})$
  $g_{ijk} = \text{or}(g_{ij(k-1)}, h_{ijk})$
- g_{1nn} is the output gate of $R(G)$.
- Constraints α:
  For the output gate: $\alpha(g_{1nn}) =$ **true**
  For the input gates: $\alpha(g_{ij0}) =$ **true** if $i = j$ or (i, j) is an edge in G else $\alpha(g_{ij0}) =$ **false**.

Example—cont'd

- Because of the constraints α on input gates there is at most one possible truth assignment T.
- It can be shown by induction on $k = 0, 1, \ldots, n$ that in this assignment the truth values of the gates correspond to their given intuitive readings.
- From this it follows:
  $R(G)$ is satisfiable iff $T(g_{1nn}) =$ **true** in the truth assignment iff there is a path from 1 to n in G without any intermediate nodes bigger than n iff there is a path from 1 to n in G.

Example. Reachability with choices

- Consider now a more challenging (search problem).
- For odd numbered nodes i (but not for 1 and n) there are two alternative edges either to the node $i + 1$ or to $i - 1$ and for the other nodes the edges are given as in G.
- Find the set of edges for the odd nodes such that there is a path from 1 to n.
- To solve this problem we can use the circuit $R(G)$ and modify it for each odd node i as follows:
  - add a subcircuit $x_i = \text{xor}(g_{i,i+1,0}, g_{i,i-1,0})$ and set $\alpha(x_i) =$ **true**;
  - remove constraints $\alpha(g_{i,i+1,0}) = t$ and $\alpha(g_{i,i-1,0}) = t'$.
- Now the modified $R(G)$ is satisfiable iff there is a set of edges for the odd nodes such that there is a path from 1 to n.
- Moreover, the set of edges is given by the gates $g_{i,i-1,0}, g_{i,i+1,0}$ true in a satisfying truth assignment.

From Circuits to CNF

- Translating Boolean Circuits to an equivalent CNF formula can lead to exponential blow-up in the size of the formula.
- Often exact equivalence is not necessary but auxiliary variables can be used as long as at least satisfiability is preserved.
- Then a linear size CNF representation can be obtained using co-called Tseitin translation where given a Boolean circuit C the corresponding CNF formula is obtained as follows
  - a new variable is introduced to each gate of the circuit,
  - the set of clauses in the normal form consist of the gate equation is written in a clausal form for each intermediate and output gate and the corresponding literal for each gate g with a constraint $\alpha(g) = t$.
- This transformation preserves satisfiability and even truth assignments in the following sense:
  if C is a Boolean circuit and Σ its Tseitin translation, then for every truth assignment T of C there is a satisfying truth assignment T' of Σ which agrees with T and vice versa.

From Circuits to CNF II

Example.



Gate equations
for non-input gates:
$v_1 \leftrightarrow (v_2 \wedge v_3)$
$v_2 \leftrightarrow (v_4 \vee v_5 \vee v_6)$
$v_3 \leftrightarrow (v_5 \leftrightarrow v_6)$

In CNF:

$$(\neg v_1 \vee v_2) \wedge (\neg v_1 \vee v_3) \wedge (v_1 \vee \neg v_2 \vee \neg v_3) \wedge$$
$$(v_2 \vee \neg v_4) \wedge (v_2 \vee \neg v_5) \wedge (v_2 \vee \neg v_6) \wedge (\neg v_2 \vee v_4 \vee v_5 \vee v_6) \wedge$$
$$(v_3 \vee v_5 \vee v_6) \wedge (v_3 \vee \neg v_5 \vee \neg v_6) \wedge (\neg v_3 \vee v_5 \vee \neg v_6) \wedge (\neg v_3 \vee \neg v_5 \vee v_6) \wedge$$
$$(\neg v_4) \text{ (for the constraint } \alpha(v_4) = \textbf{false})$$