BOOLEAN LOGIC

- Syntax
- Semantics
- Normal forms
- Satisfiability and validity
- Boolean functions and expressions
- Boolean circuits

(C. Papadimitriou: *Computational complexity*, Chapter 4)

© 2006 TKK, Laboratory for Theoretical Computer Science

Motivation

- Logic involves interesting computational problems.
- Logic is "the calculus of computer science":

  digital circuit design, programming language semantics, specification and verification, constraint programming, logic programming, databases, artificial intelligence, knowledge representation, machine learning, ...
- In computational complexity theory:

  Computational problems from logic are of central importance; they can be used to express computation at various levels.

  This leads to important connections between complexity concepts and actual computational problems.

© 2006 TKK, Laboratory for Theoretical Computer Science

1. Syntax

- The syntax of Boolean logic (i.e. the set of well-formed Boolean expressions) is based on the following symbols:
  - Boolean *variables* (or *atoms*): $X = \{x_1, x_2, \ldots\}$.
  - Boolean *connectives*: $\vee$, $\wedge$, and $\neg$.
- The set of Boolean expressions (formulae) is the smallest set such that all Boolean variables are Boolean expressions and if ϕ_1 and ϕ_2 are Boolean expressions, so are $\neg\phi_1$, $(\phi_1 \wedge \phi_2)$, and $(\phi_1 \vee \phi_2)$.
- An expression of the form x_i or $\neg x_i$ is called a *literal* where x_i is a Boolean variable.

Example. $((x_1 \vee x_2) \wedge \neg x_3)$ is a Boolean expression but $((x_1 \vee x_2)\neg x_3)$ is not.

© 2006 TKK, Laboratory for Theoretical Computer Science

Some notational conventions

- Simplified notation: $(((x_1 \vee \neg x_3) \vee x_2) \vee (x_4 \vee (x_2 \vee x_5)))$ is written as $x_1 \vee \neg x_3 \vee x_2 \vee x_4 \vee x_2 \vee x_5$ or $x_1 \vee \neg x_3 \vee x_2 \vee x_4 \vee x_5$.
- Disjunctions and conjunctions involving n members:
  - $\bigvee_{i=1}^{n} \varphi_i$ stands for $\varphi_1 \vee \cdots \vee \varphi_n$.
  - $\bigwedge_{i=1}^{n} \varphi_i$ stands for $\varphi_1 \wedge \cdots \wedge \varphi_n$.
- Frequently appearing abbreviations:
  - An implication $\phi_1 \rightarrow \phi_2$ stands for $\neg\phi_1 \vee \phi_2$.
  - An equivalence $\phi_1 \leftrightarrow \phi_2$ stands for $(\neg\phi_1 \vee \phi_2) \wedge (\neg\phi_2 \vee \phi_1)$.

© 2006 TKK, Laboratory for Theoretical Computer Science

2. Semantics

How to interpret Boolean expressions?

- Boolean expressions are propositions that are either true or false.
  They speak about a world where certain atomic proposition (Boolean variables) are either true or false.
  This induces truth values for Boolean expressions as follows.
- A truth assignment T is mapping from a finite subset $X' \subset X$ to the set of truth values $\{\mathbf{true}, \mathbf{false}\}$.
- Let $X(\phi)$ be the set of Boolean *variables appearing in* ϕ.
  Definition. A truth assignment $T : X' \to \{\mathbf{true}, \mathbf{false}\}$ is *appropriate* to ϕ if $X(\phi) \subseteq X'$.

© 2006 TKK, Laboratory for Theoretical Computer Science

Satisfaction relation

- Let a truth assignment $T : X' \to \{\mathbf{true}, \mathbf{false}\}$ be appropriate to ϕ, i.e., $X(\phi) \subseteq X'$.
- $T \models \phi$ (T *satisfies* ϕ) is defined inductively as follows:
  If ϕ is a variable from X', then $T \models \phi$ iff $T(\phi) = \mathbf{true}$.
  If $\phi = \neg\phi_1$, then $T \models \phi$ iff $T \not\models \phi_1$.
  If $\phi = \phi_1 \wedge \phi_2$, then $T \models \phi$ iff $T \models \phi_1$ and $T \models \phi_2$.
  If $\phi = \phi_1 \vee \phi_2$, then $T \models \phi$ iff $T \models \phi_1$ or $T \models \phi_2$.

Example. Let $T(x_1) = \mathbf{true}$, $T(x_2) = \mathbf{false}$.
Then $T \models x_1 \vee x_2$ but $T \not\models (x_1 \vee \neg x_2) \wedge (\neg x_1 \wedge x_2)$.

© 2006 TKK, Laboratory for Theoretical Computer Science

Logical equivalence

Definition. Expressions ϕ_1 and ϕ_2 are logically *equivalent* ($\phi_1 \equiv \phi_2$) iff for all truth assignments T appropriate to both of them,

$$T \models \phi_1 \text{ iff } T \models \phi_2.$$

Example.
$(\phi_1 \vee \phi_2) \equiv (\phi_2 \vee \phi_1)$
$((\phi_1 \wedge \phi_2) \wedge \phi_3) \equiv (\phi_1 \wedge (\phi_2 \wedge \phi_3))$
$\neg\neg\phi \equiv \phi$
$((\phi_1 \wedge \phi_2) \vee \phi_3) \equiv ((\phi_1 \vee \phi_3) \wedge (\phi_2 \vee \phi_3))$
$\neg(\phi_1 \wedge \phi_2) \equiv (\neg\phi_1 \vee \neg\phi_2)$
$(\phi_1 \vee \phi_1) \equiv \phi_1$

© 2006 TKK, Laboratory for Theoretical Computer Science

3. Normal Forms

Theorem. Every Boolean expression is equivalent to one in conjunctive (disjunctive) normal form CNF (DNF).

- These forms are defined by
  CNF: $(l_{11} \vee \cdots \vee l_{1n_1}) \wedge \cdots \wedge (l_{m1} \vee \cdots \vee l_{mn_m})$
  DNF: $(l_{11} \wedge \cdots \wedge l_{1n_1}) \vee \cdots \vee (l_{m1} \wedge \cdots \wedge l_{mn_m})$
  where each l_{ij} is a literal (Boolean variable or its negation).
- A disjunction $l_1 \vee \cdots \vee l_n$ of literals is called a *clause*.
- A conjunction $l_1 \wedge \cdots \wedge l_n$ of literals is called an *implicant*.
- We can assume that normal forms do not have repeated clauses/implicants or repeated literals in clauses/implicants.
  Example. $(\neg x_1 \vee \neg x_1 \vee x_2) \equiv (\neg x_1 \vee x_2)$.

© 2006 TKK, Laboratory for Theoretical Computer Science

CNF/DNF transformation

Any Boolean expression can be transformed into CNF/DNF as follows.

- Remove $\leftrightarrow$ and $\rightarrow$:

$$\alpha \leftrightarrow \beta \quad \leadsto \quad (\neg\alpha \vee \beta) \wedge (\neg\beta \vee \alpha) \quad (1)$$
$$\alpha \rightarrow \beta \quad \leadsto \quad \neg\alpha \vee \beta \quad (2)$$

- Push negations in front of Boolean variables:

$$\neg\neg\alpha \quad \leadsto \quad \alpha \quad (3)$$
$$\neg(\alpha \vee \beta) \quad \leadsto \quad \neg\alpha \wedge \neg\beta \quad (4)$$
$$\neg(\alpha \wedge \beta) \quad \leadsto \quad \neg\alpha \vee \neg\beta \quad (5)$$

☞ The result is a mixed conjunction and disjunction of literals.

© 2006 TKK, Laboratory for Theoretical Computer Science

CNF/DNF transformation—cont'd

The next phase depends on the normal form being pursued:

- For a CNF, move $\wedge$ connectives outside $\vee$ connectives:

$$\alpha \vee (\beta \wedge \gamma) \quad \leadsto \quad (\alpha \vee \beta) \wedge (\alpha \vee \gamma) \quad (6)$$
$$(\alpha \wedge \beta) \vee \gamma \quad \leadsto \quad (\alpha \vee \gamma) \wedge (\beta \vee \gamma) \quad (7)$$

- For a DNF, move $\vee$ connectives outside $\wedge$ connectives:

$$\alpha \wedge (\beta \vee \gamma) \quad \leadsto \quad (\alpha \wedge \beta) \vee (\alpha \wedge \gamma) \quad (8)$$
$$(\alpha \vee \beta) \wedge \gamma \quad \leadsto \quad (\alpha \wedge \gamma) \vee (\beta \wedge \gamma) \quad (9)$$

Note: Normal forms can be exponentially bigger than the original expression in the worst case.

Example. Consider deriving a CNF for $(x_1 \wedge \neg x_1) \vee \ldots \vee (x_n \wedge \neg x_n)$.

© 2006 TKK, Laboratory for Theoretical Computer Science

Example

Transform $(x_1 \vee x_2) \rightarrow (x_2 \leftrightarrow x_3)$ into CNF.

$(x_1 \vee x_2) \rightarrow (x_2 \leftrightarrow x_3)$ (1)

$\neg(x_1 \vee x_2) \vee (x_2 \leftrightarrow x_3)$ (2)

$\neg(x_1 \vee x_2) \vee ((\neg x_2 \vee x_3) \wedge (\neg x_3 \vee x_2))$ (4)

$(\neg x_1 \wedge \neg x_2) \vee ((\neg x_2 \vee x_3) \wedge (\neg x_3 \vee x_2))$ (7)

$(\neg x_1 \vee ((\neg x_2 \vee x_3) \wedge (\neg x_3 \vee x_2))) \wedge (\neg x_2 \vee ((\neg x_2 \vee x_3) \wedge (\neg x_3 \vee x_2)))$ (6)

$((\neg x_1 \vee (\neg x_2 \vee x_3)) \wedge (\neg x_1 \vee (\neg x_3 \vee x_2)))$
$\wedge\ (\neg x_2 \vee ((\neg x_2 \vee x_3) \wedge (\neg x_3 \vee x_2)))$ (6)

$((\neg x_1 \vee (\neg x_2 \vee x_3)) \wedge (\neg x_1 \vee (\neg x_3 \vee x_2)))$
$\wedge\ ((\neg x_2 \vee (\neg x_2 \vee x_3)) \wedge (\neg x_2 \vee (\neg x_3 \vee x_2)))$ (Simplification)

$(\neg x_1 \vee \neg x_2 \vee x_3) \wedge (\neg x_1 \vee \neg x_3 \vee x_2) \wedge (\neg x_2 \vee \neg x_2 \vee x_3) \wedge (\neg x_2 \vee \neg x_3 \vee x_2)$

© 2006 TKK, Laboratory for Theoretical Computer Science

4. Satisfiability and Validity

➤ A Boolean expression ϕ is *satisfiable* iff
there is a truth assignment T appropriate to it such that $T \models \phi$.

➤ A Boolean expression ϕ is *valid*/*tautology* (denoted by $\models \phi$) iff
for every truth assignment T appropriate to it, $T \models \phi$.

➤ The interconnection of satisfiability and validity:

$$\models \phi \text{ iff } \neg\phi \text{ is unsatisfiable.}$$

➤ Moreover, for any Boolean expressions ψ_1 and ψ_2,

$$\psi_1 \equiv \psi_2 \text{ iff } \models \psi_1 \leftrightarrow \psi_2 \text{ iff } \neg(\psi_1 \leftrightarrow \psi_2) \text{ is unsatisfiable.}$$

☞ Satisfiability forms a fundamental computational problem.

© 2006 TKK, Laboratory for Theoretical Computer Science

Satisfiability Problem

- *SAT problem*: Given φ in CNF, is φ satisfiable?

  Example. $(x_1 \vee \neg x_2) \wedge \neg x_1$ is satisfiable but $(x_1 \vee \neg x_2) \wedge \neg x_1 \wedge x_2$ is unsatisfiable.

- SAT can be solved in $O(n^2 2^n)$ time (e.g., truth table method).

- SAT $\in$ **NP** but SAT $\in$ **P** remains open!

A nondeterministic Turing machine for $\varphi \in$ SAT:
for all variables x in φ **do**
  choose nondeterministically: $T(x) :=$ **true** or $T(x) :=$ **false**;
if $T \models \varphi$ **then** return "yes" **else** return "no"

© 2006 TKK, Laboratory for Theoretical Computer Science

Horn clauses

- An interesting special case of SAT concerns *Horn clauses*, i.e., clauses (disjunction of literals) with *at most one positive literal*.

  Example. $\neg x_1 \vee x_2 \vee \neg x_3$ and $\neg x_1 \vee \neg x_3$, x_2 are Horn clauses but $\neg x_1 \vee x_2 \vee x_3$ is not.

- A Horn clause with a positive literal is called an *implication* and can be written as $(x_1 \wedge x_3) \rightarrow x_2$ (or $\rightarrow x_2$ when there are no negative literals).

- HORNSAT problem:
  Given a conjunction of Horn clauses, is it satisfiable?

© 2006 TKK, Laboratory for Theoretical Computer Science

Polynomial Time Algorithm for HORNSAT

Algorithm $hornsat(S)$
/* Determines whether $S \in$ HORNSAT */
$T := \emptyset$ /* T is the set of true atoms */
repeat
  if there is an implication $(x_1 \wedge x_2 \wedge \cdots \wedge x_n) \rightarrow y$ in S
    such that $\{x_1, \ldots, x_n\} \subseteq T$ but $y \notin T$ **then**
    $T := T \cup \{y\}$
until T does not change
if for all purely negative clauses $\neg x_1 \vee \cdots \vee \neg x_n$ in S,
  there is some literal $\neg x_i$ such that $x_i \notin T$ **then**
  return S is satisfiable
else return S is not satisfiable

☞ HORNSAT $\in$ **P**.

© 2006 TKK, Laboratory for Theoretical Computer Science

5. Boolean Functions and Expressions

- An n-ary Boolean function is a mapping $\{\mathbf{true}, \mathbf{false}\}^n \rightarrow \{\mathbf{true}, \mathbf{false}\}$.

  Example. The connectives $\vee$, $\wedge$, $\rightarrow$, and $\leftrightarrow$ can be viewed as binary Boolean functions and $\neg$ is a unary function.

- Similarly, any Boolean expression ϕ can be interpreted as an n-ary Boolean function f_ϕ where $n = |X(\phi)|$.

- A Boolean expression ϕ with variables $x_1, \ldots, x_n$ *expresses* the n-ary function f if for any n-tuple of truth values $\mathbf{t} = (t_1, \ldots, t_n)$,

$$f(\mathbf{t}) = \begin{cases} \mathbf{true}, & \text{if } T \models \phi. \\ \mathbf{false}, & \text{if } T \not\models \phi. \end{cases}$$

  where T satisfies $T(x_i) = t_i$ for every $i = 1, \ldots, n$.

© 2006 TKK, Laboratory for Theoretical Computer Science

Proposition. Any n-ary Boolean function f can be expressed as a Boolean expression ϕ_f involving variables $x_1, \ldots, x_n$.

- The idea: model the rows of the truth table giving **true** as a disjunction of conjunctions.
- Let F be the set of all n-tuples $\mathbf{t} = (t_1, \ldots, t_n)$ with $f(\mathbf{t}) = \mathbf{true}$.
- For each $\mathbf{t}$, let $D_\mathbf{t}$ be a conjunction of literals x_i if $t_i = \mathbf{true}$ and $\neg x_i$ if $t_i = \mathbf{false}$.
- Let $\phi_f = \bigvee_{\mathbf{t} \in F} D_\mathbf{t}$
- Note that ϕ_f may get big in the worst case: $O(n2^n)$.

☞ Not all Boolean functions can be expressed concisely.

Example.

x_1	x_2	f
0	0	0
0	1	1
1	0	1
1	1	0

$\phi_f = (\neg x_1 \wedge x_2) \vee (x_1 \wedge \neg x_2)$.

© 2006 TKK, Laboratory for Theoretical Computer Science

6. Boolean Circuits

A more economical way to represent Boolean functions?

Syntax:

- A graph $C = (V, E)$ where $V = \{1, 2, \ldots, n\}$ is the set of gates and C must be acyclic ($i < j$ for all edges $(i, j) \in E$).
- All gates i have a sort $s(i) \in \{\mathbf{true}, \mathbf{false}, \wedge, \vee, \neg\} \cup \{x_1, x_2, \ldots\}$.
  - If $s(i) \in \{\mathbf{true}, \mathbf{false}\} \cup \{x_1, x_2, \ldots\}$, the indegree of i is 0 (inputs).
  - If $s(i) = \neg$, the indegree of i 1.
  - If $s(i) \in \{\vee, \wedge\}$, the indegree of i is 2.
- Node n is the output of the circuit.

© 2006 TKK, Laboratory for Theoretical Computer Science

Semantics

A truth assignment is a function $T : X(C) \to \{\mathbf{true}, \mathbf{false}\}$ where $X(C)$ is the set of variables appearing in a circuit C.

The truth value $T(i)$ for each gate i is defined inductively:

- If $s(i) = \mathbf{true}$, $T(i) = \mathbf{true}$ and if $s(i) = \mathbf{false}$, $T(i) = \mathbf{false}$.
- If $s(i) \in X(C)$, then $T(i) = T(s(i))$.
- If $s(i) = \neg$, then $T(i) = \mathbf{true}$ if $T(j) = \mathbf{false}$, otherwise $T(i) = \mathbf{false}$ where (j, i) is the unique edge entering i.
- If $s(i) = \wedge$, then $T(i) = \mathbf{true}$ if $T(j) = T(j') = \mathbf{true}$ else $T(i) = \mathbf{false}$ where (j, i) and (j', i) are the two edges entering i.
- If $s(i) = \vee$, then $T(i) = \mathbf{true}$ if $T(j) = \mathbf{true}$ or $T(j') = \mathbf{true}$ else $T(i) = \mathbf{false}$ where (j, i) and (j', i) are the two edges to i.
- $T(C) = T(n)$, i.e. the *value of the circuit* C.

© 2006 TKK, Laboratory for Theoretical Computer Science

Boolean circuits vs. Boolean expressions

- For each Boolean circuit C, there is a corresponding Boolean expression ϕ_C.
- For each Boolean expression ϕ, there is a corresponding Boolean circuit C_ϕ such that for any T appropriate for both,

  $$T(C_\phi) = \mathbf{true} \text{ iff } T \models \phi.$$

  Idea: just introduce a new gate for each subexpression of ϕ.
- Notice that Boolean circuits allow shared subexpressions but Boolean expressions do not.

© 2006 TKK, Laboratory for Theoretical Computer Science

Computational problems related with Boolean circuits

- CIRCUIT SAT:
  Given a circuit C, is there a truth assignment $T : X(C) \to \{\mathbf{true}, \mathbf{false}\}$ such that $T(C) = \mathbf{true}$?
- CIRCUIT SAT $\in \mathbf{NP}$.
- CIRCUIT VALUE:
  Given a circuit C with no variables, is it the case that $T(C) = \mathbf{true}$?
- CIRCUIT VALUE $\in \mathbf{P}$.
  (No truth assignment is needed as $X(C) = \emptyset$).

© 2006 TKK, Laboratory for Theoretical Computer Science

Circuits computing Boolean functions

- A Boolean circuit with variables $x_1, \ldots, x_n$ *computes* an n-ary Boolean function f if for any n-tuple of truth values $\mathbf{t} = (t_1, \ldots, t_n)$, $f(\mathbf{t}) = T(C)$ where $T(x_i) = t_i$ for $i = 1, \ldots, n$.
- Any n-ary Boolean function f can be computed by a Boolean circuit involving variables $x_1, \ldots, x_n$.
- Not every Boolean function has a concise circuit computing it.

Theorem. For any $n \geq 2$ there is an n-ary Boolean function f such that no Boolean circuit with $\frac{2^n}{2n}$ or fewer gates can compute it.

However, all natural families of Boolean functions seem to need only a linear number of gates to compute!

© 2006 TKK, Laboratory for Theoretical Computer Science

Learning Objectives

- You should deeply understand the syntax and semantics of Boolean expressions — including their use in practice.
- The relationship/difference between Boolean expressions and circuits.
- Knowing the idea of representing Boolean functions in terms of Boolean expressions and circuits.
- Four computational problems related with Boolean logic and circuits: SAT, HORNSAT, CIRCUIT SAT, and CIRCUIT VALUE.

© 2006 TKK, Laboratory for Theoretical Computer Science